General Specifications

| Description | comoutions | ScanSnap iX100 | |
|---------------------------|------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--|
| Scanner type | | CDF (Continuous Document Feeding), Simplex sheetfeed two-way paper path (Straight path, U-turn path) | |
| Scanning mode | S | Color, grayscale, monochrome, automatic (color / grayscale / monochrome detection) | |
| Image sensor | | CIS (Contact Image Sensor) x 1 | |
| Light source | | 3 Color LED (Red / Green / Blue) | |
| Optical resolution | on | 600 dpi | |
| Auto mode (default) *2 | | | |
| Scanning speed *1 | Normal mode (150 dpi) Better mode (200 dpi) | 5.2 seconds / page | |
| (Å4 portrait) | Best mode (300 dpi) | | |
| | Excellent mode (600 dpi) | 20.4 seconds / page | |
| Desument size | Normal mode | A4, A5, A6, B5, B6, Business card, Post card, Letter, Legal and Custom sizes (Max: 216 x 360 mm (8.5 x 14.17 in.), Min: 25.4 x 25.4 mm (1 x 1 in.)), Automatically recognizes document size | |
| Document size | Normal mode with Carrier sheet | Use of a carrier sheet permits the scanning of A3, B4, double letter and photographs as well as the document sizes that are listed above. | |
| | Long paper scanning *4 | Max: 216 x 863 mm (8.5 x 34 in.) (300 dpi or less) | |
| Paper weight (Thickness) | | 52.3 to 209.3 g/m², or 14 to 56 lb (Straight path) 52.3 to 80 g/m², or 14 to 20 lb (U-turn path) Card Portrait or Landscape (Straight path) Non-embossed: 0.76 mm or less Embossed: 0.76 + 0.48 mm (ISO7810 Conforming) | |
| Paper setting | | Front side up | |
| Continuous sca | nning | 260 sheets (A4, color, simplex, 300 dpi, battery operated) ∗ ₅ | |
| Interface *6 | | USB 2.0 (USB 1.1 compatible) | |
| Power source | | Li-ion Batterry (3.7 V / 720 mAh) | |
| Power requirem | ent | 5 V / 0.5 A (x 1port) | |
| Power consumption *7 | | During operation: 4.7 W or less During sleep mode: 2.2 W or less During Auto Standby (OFF) mode: Less than 0.5 W | |
| Operation environment | | Temperature: 5 to 35 °C (41 to 95 °F) Relative humidity: 20 to 80% (Non-condensing) | |
| Dimensions (W x D x H) *8 | | 273 x 47.5 x 36 mm (10.74 x 1.87 x 1.42 in.) | |
| Device weight | | 400 g (0.88 lb) | |
| Environmental compliance | | ENERGY STAR [®] compliant / RoHS | |
| Multifeed detect | tion | None | |
| Driver | | ScanSnap specific driver ●Windows [®] : Does not support TWAIN / ISIS™ ●Mac OS: Does not support TWAIN | |

*1 Scanning speeds may vary due to the system environment used. Scanning speed means the time from "Start feeding document" to "Finish output document" after pre-pick and pushing Scan button. In case of "From pushing Scan button Warm-up time is added. Wwarm-up time: From Ready status: Less than 2 seconds. From Chute Cover Closed Status Less than 3 seconds *2 Documents measuring approximately 148 mm in length or less are scanned in "Best mode" while other documents are scanned in "Better mode". *3 Automatically stitch a two-page spread when scanning i folded A3, B4 or Double letter size document one side at a time. The image is automatically stitched only if texts or the side at a time. lidegrams cover across the two-page spread. ***4** The X100 is capeable of scanning documents that exceed A4 size in length. This function is available for all modes except for "Excellent mode". ***5** The number of sheets that can be scanned when connected to a computer valW-Fi with fully charged battery. The number of sheets may vary due to the system environment used, usage method and repeated charging. ***6** Computer withertwo **X8** 0 will low as USB 2.0 will over a USB 2.0 will over a USB 2.0 will exceed A4 size in guaranteed only with USB cable provided with product. ***7** When operating with battery. ***8** When churter is closed.

Software

| | Windows® | Mac OS | |
|------------------------------------------------------------------|------------------------------------|------------------------------------------------|--|
| Driver *1 ScanSnap Manager V6.3 (TWAIN / ISIS™ not supported) | | ScanSnap Manager V6.3 (TWAIN not supported) | |
| | ScanSnap Organizer V5.2 | ScanSnap Organizer V1.1 | |
| Applications | CardMinder™ V5.2 | CardMinder™ V5.2 | |
| Applications | ABBYY FineReader for ScanSnap™ 5.0 | ABBYY FineReader for ScanSnap™ 5.0 | |
| | Scan to Microsoft® SharePoint® | - | |
| *1 TWAIN or ISIS™ applications cannot be used directly | | | |

Included items

| e dottang otta tod e oott ap b t b t oth e oob oablo | | Getting started | Set-up DVD-ROM | USB cable | |
|------------------------------------------------------|--|-------------------------------------|----------------|-----------|--|
|------------------------------------------------------|--|-------------------------------------|----------------|-----------|--|

Consumables

| Description | Part number | Remarks |
|-------------|--------------|----------------------------------------|
| Cleaner F1 | PA03950-0352 | 100 ml bottle Used to clean rollers |
| OL | | 1 page (01 shasts) |

This scanner is designed to digitize materials that can be reproduced lawfully, in accordance with applicable copyright regulations and other laws. ScanSnap users are responsible for how they use this scanner. It is imperative that ScanSnap users comply with all applicable local rules and laws, including, without limitation, copyright laws when using this scanner.

*ABBYY and FineReader are trademarks of ABBYY Software, Ltd. which may be registered in some jurisdictions. ABBYY™ FineReader™ Engine ©2011 ABBYY, OCR by ABBYY. *Evernote is a registered trademark or trademark of Evernote Corporation. *Coogle and Google Docs are registered trademarks or trademarks of Google Inc. *Intel, Pentium, and Intel Core are trademarks or registered trademarks of Intel Corporation in the United States and other countries. *KISIS™ is a registered trademark of EVER Corporation in the United States. *Mac. Mac OS, Mac Iogo and iPhoto are trademarks of Apple Inc. *Microsoft, Windows, Windows Vista, Excel, PowerPoint and SharePoint are either registered trademarks or trademarks of Intel Corporation in the United States. *Mac OS, Mac Iogo and iPhoto are trademarks of Apple Inc. *Microsoft Other countries. *Word is the products of Microsoft Corporation in the United States. *AR. *PowerPC is a registered trademarks or trademarks of salesforce.com, inc. in the United States and other countries, or both. *Salesforce and Salesforce CRM are registered trademarks of salesforce.com, inc. in the United States and Other countries. *ScanSnap, ScanSnap Iogo, ScanSnap Manager, ScanSnap Organizer and CardMinder are registered trademarks of PFU LIMITED in Japan. *Other company names and product names are the trademarks or registered trademarks of the respective companies.

For more ScanSnap related information, visit our Web site at : http://scansnap.fujitsu.com/

A Safety Precautions Be sure to carefully read all safety precautions prior to using this product and use this device as instructed. Do not place this device in wet, moist, steamy, dusty or oily areas. Using this product under such conditions may result in electrical shock, fire or damage to this product.

Specifications are subject to change without notice.

ScanSnap iX100 System Requirements Windows[®]

| Compatible operating systems | | Windows® 8 / 8.1 (32-bit / 64-bit) | Windows [®] 7 (32-bit / 64-bit) *1 | Windows Vista™ (32-bit / 64-bit) *2 |
|--------------------------------|----------------------------------------------------------------------|-----------------------------------------------|------------------------------------------------|----------------------------------------|
| | ScanSnap Manager V6.3 | Supported | Supported | Supported |
| Driver / Applications *3 | ScanSnap Organizer V5.2 | Supported | Supported | Supported |
| | CardMinder [™] V5.2 | Supported | Supported | Supported |
| | ABBYY FineReader for ScanSnap™ 5.0 | Supported | Supported | Supported |
| | Scan to Microsoft SharePoint 3.4 Scan to Microsoft SharePoint 5.0 | Supported | Supported | Supported |
| | CPU *5 | Intel [®] Core™ i5 2.5 GHz or higher | | |
| | Memory capacity *5 | 4 GB or more | | |
| Hardware requirements | Display | 1,024 x 768 pixels or higher | 800 x 600 pixels or higher | |
| | Disk capacity *6 | 2,690 MB or more of free hard disk space | | disk space |
| | DVD-ROM drive | Required for installation | | on |
| | USB port *5 *7 | USB 2.0 / USB 1.1 | | |

In the second point of an interview of the second point of the

Mac OS

| Compatible operating systems | | OS X v10.9 *1 | OS X v10.8 *2 | Mac OS X v10.7 *3 |
|--------------------------------|---------------------------------------|-----------------------------------------------|---------------|-------------------|
| | ScanSnap Manager V6.3 | Supported | Supported | Supported |
| Driver / | ScanSnap Organizer V1.1 | Supported | Supported | Supported |
| Applications | CardMinder [™] V5.2 | Supported | Supported | Supported |
| | ABBYY FineReader for ScanSnap™ 5.0 | Supported | Supported | Supported |
| Hardware requirements ∗5 | CPU *6 | Intel [®] Core™ i5 2.5 GHz or higher | | |
| | Memory capacity *6 | 4 GB or more | | |
| | Display | 1,024 x 768 pixels or higher | | |
| | Disk capacity | 1,930 MB or more of free hard disk space | | |
| | DVD-ROM drive | Required for installation | | |
| | USB port *6 *7 | USB 2.0 / USB 1.1 | | |
| | | | | |

*1 OS X v10.9.1 or later recommended. *2 OS X v10.8.5 recommended. *3 Mac OS X v10.7.5 recommended. *4 For the latest support information, visit the ScanSnap homepage. *5 The ScanSnap device may not work if the connected computer does not meet this requirement. *6 Scanning peeds may drop if recommended CPU, memory capacity and USB 1.1 requirements are not met. *7 When the ScanSnap is connected to a USB 3.0 port, the port operates as a USB 2.0 port. *System requirements may change depending on the duration of support and the support policy of the companies that make the software listed in the table above.

Options

| Description | Part number | Remarks | |
|---------------------------------|--------------------------------------|------------------------------------------------------------------------------------------------------------------------------|--|
| | PA03010-6571 USA, Canada & Taiwan | | |
| | PA03010-6581 EMEA, England | | |
| | PA03010-6591 China | | |
| AC adapter | PA03010-6601 Korea | The AC adapter may vary depending on the cour where you purchased the ScanSnap and the specifications of the ScanSnap. | |
| | PA03010-6611 Australia | | |
| | PA03010-6621 India | | |
| | PA03010-6631 Brazil | | |
| ScanSnap iX100 Case *1 | PA03688-0001 | | |
| ScanSnap iX100 Soft Case *1 | PA03688-0011 | Intended for ScanSnap iX100 | |
| ScanSnap Carrier Sheets *2 | PA03360-0013 | 5 Carrier Sheets Intended for ScanSnap iX500, iX100, S1500, S1500M, S1100i, S1100 | |
| *1 This product has been especi | ally designed for stori | ng and carrying ScanSnap iX100. Please note that this produc | |


It it is product has been especially designed for storing and carrying ScanSnap X100. Please note that this products not guaranteed to withstand damage by excessive shock or external pressure. *2 Although ScanSnap Carrier Sheets have a listed lifespan of 500 scans, the lifespan may vary with usage. ScanSnap Carrier sheets are interded to scan paper documents with weights of 127 g/m² or less. They also support the scanning of folded documents that are is large as 216 x 297 mm.




PFU LIMITED, a Fujitsu company, has determined that this product neets the ENERGY STAR® guidelines for energy efficiency. ENERGY STAR® is a registered trademark of the United States.

iX100

Simple, Speedy & Compact. From Paper to PDF in One Touch!





©2014 PFU LIMITED Printed in some country 2014.08 U-155 AMN 50S





New features

- The world's lightest compact body
- The fastest mobile scanner in its class
- No need to switch the Wi-Fi mode manually
- Battery operated without the necessity of cable connection
- Dual Scan scanning 2 small sized documents at the same time
- Automatically stitch a two-page spread

Bundle software

CardMinder (Win / Mac)



Productivity unleashed

The world's lightest compact body*

The iX100 is only 400g in weight even with built-in battery and Wi-Fi connectivity. The compact and light body make it a convenient companion when traveling or on the road.

*Based on the investigation by PFU LIMITED on A4 document feed type scanner with built-in battery and Wi-Fi connectivity. (as of April 1st, 2014)

The fastest mobile scanner in its class*

The iX100 is the fastest A4 sheetfeed scanner with built-in battery and Wi-Fi connectivity; it can scan at a snappy speed of 5.2 seconds/ page for color A4 document at a resolution of up to 300 dpi.

*Based on the investigation by PFU LIMITED on A4 document feed type scanner with built-in battery and Wi-Fi connectivity. (as of April 1st, 2014)

Battery operated without the necessity of cable connection

The iX100 can be scanned without the cables, so you can use it when power supply is unavailable or limited. The scanner is always ready to be used immediately when needed.

Scans plastic cards and other various document types*

In addition to standard paper types, the iX100 can scan plastic cards like the ones used for membership IDs. *ISO 7810 card types (including embossed cards)

Two selectable paper paths

Depending on the document to be scanned, there are two ways that it can exit the iX100.

Straight path

Most suitable for scanning post cards, photos, business cards, plastic cards*, ScanSnap Carrier Sheet (Option), and common office paper. *This applies to standard ISO 7810 ID-1 card types.

Output Description

Most suitable for scanning common office paper and you do not need extra space for the document output.

Fast and flexible application of scanned data with Quick Menu

Users just choose what they want to do from the Quick Menu, which appears after a document has been scanned. iX100's Quick Menu is perfect for everyone, even the complete novice!

Quick Menu (Mac OS)

Quick Menu (Windows®)



Continuous Document Feeding (CDF Function)

The Continuous Document Feeding function allows you to insert pages one after another without pressing any extra button by detecting when a sheet enters and exits the iX100.

Scanning a two-sided document using the CDF Function











Feed guide

70

Output

guide

convert the data to a PDF image file.



No need to switch the Wi-Fi mode manually for comfortable scanning anywhere, anytime

The ScanSnap iX100 is equipped with built-in Wi-Fi which is able to automatically detect and switch to the network environment at home, in the office or on the go. You only need to set up initially and iX100 can be scanned wirelessly directly to any platform even without Wi-Fi network in the environment.

•At home: Connect via the access point of the router at home In the office: Connect to the secured Wi-Fi network via IEEE802.1X (network device authentication)

On the road: Connect via Direct Connect mode (do not need an access point)



New features for quick digitization

•Dual scan - scanning 2 small sized documents at the same time

With this new feature, you can scan 2 small sized documents such as business card and receipt at the same time. Simply insert documents continuously to the paper feeding entry to greatly reduce your scanning time and lead to increased efficiency.




Automatically stitch a two-page spread

Even documents larger than A4 size can be scanned without any extra effort. Just fold the large documents in half and the iX100 will automatically stitch the diagram or chart that is spread across two pages after scanning.

Set a page of your document face-up into the iX100 and push the Scan button to start the scanning

2 The iX100 proceeds to scan the front side of that page

of the scanner which has its paper path set to the U-turn positior



After you finish scanning your document, press the Scan button again to end the scanning and



Easily links documents to clouds

You can scan nearly effortlessly to Evernote, Google Docs, Salesforce, SugarSync and Dropbox, and then conveniently browse the data from computers, tablets or smartphones - anywhere, anytime.

Introducing ScanSnap Folder [Windows[®]]

ScanSnap folder is created in the Windows OS, so you can scan directly to the ScanSnap folder when you select ScanSnap folder in the file attachment selection dialog. In this way, you do not have to save the data in the computer beforehand and the operation is smooth and effective.



Automated features for near effortless scanning

The iX100 features a powerful set of automated image processing functions including Auto deskew, Auto orientation, and Auto color detection. These functions make pre-scan work like sorting pages and changing scan settings unnecessary, so you can scan your documents with minimal effort.

Efficiently organize data from scanned business cards

Business card organizer software

CardMinder[™] V5.2 [Windows[®]]

CardMinder[™] V5.2 [Mac 0S]

- Scan your collection of business cards into easy to navigate digital business card holders.
- Import the data from your scanned business cards into Excel, Outlook, Address book (Mac OS) and other database programs for fast referencing and application.

Generates Microsoft® Word, Excel®, **PowerPoint®** files

Top-class OCR engine

ABBYY FineReader for ScanSnap[™] 5.0 [Windows®] **ABBYY FineReader for ScanSnap[™] 5.0** [Mac OS]

Smoothly scan and convert paper documents into Word, Excel® and PowerPoint® documents.

*Only Microsoft[®] Word and Excel[®] are available for Mac OS. *Generated images and text may vary from the original

Carrying case (Option)

Two convenient carrying cases intended for the iX100 are available. (See disclaimer under "Option" in the next page.)

ScanSnap iX100 Soft Case